

Панель GE600x600-45W Warm White



Line-Up:

Category	Specifications	Unit
Watts	46	W
Lumens per Watt (Efficacy)	70	Lm/W
Light Output	3600	lm
Light Color (CCT)	3000	K
Beam Angle	120	°(degree)
Color Accuracy (CRI)	80	Ra
Product Weight	4.5	kg
Dimension (mm)	596*596	mm
Rating Life	35 000	H
Base	CON	
Input Voltage (AC)	220	V


Technical Specifications:

Item	Test Conditions	Min.	Typ.	Max.
Input Voltage (V, rms)	AC	110	220	240
Input Current (mA, rms)	AC (220V)	---	209	---
Input Power (W, rms)	AC (All)	---	46	---
Input Frequency (Hz)	AC	---	50Hz/60Hz	---
Power Factor (PF)	AC (All)	≥0.9		
Output Voltage (V)	DC	30	31	32
Output Current (A)	DC	1.225	1.250	1.275
Output Power (W)	DC	36.75	38.75	40.8


Environmental Requirements:

Specifications	Values
Operational Temperature Range	-20 ~ +40°C
Preservation Temperature Range	-20 ~ +90°C
Operational Humidity Range	95% Rh or below (@ -20 ~ +40°C)
Installation Area	Indoor (Counter, Residential, Commercial, etc)


Luminance Intensity Distribution:




Cone Lux Diagram:




DRAWING:




INSTALLATION INSTRUCTIONS:



WIRING DIAGRAM:



PACKAGE:



Product Dimension	L596 x W596 x H11 mm
Net Weight	4.5 kg
Size of box	L685 X W635 X H50 mm
Gross Weight	5.5kg
Size of Carton	L715 x W665x H275 mm
Qty/ Carton	4PCS
Weight/ Carton	24.3kg

NOTICE FOR USER:

- Do not open non user serviceable parts inside.
- Products not suitable for high temperature.
- You have to wait until the lights cool down when replace the light.
- Switch off the power before replacement,inspection,installation.
- Refrain from cleaning the PANEL with water.
- Indoor use only.
- This product is free voltage AC100-240 volts.
- Do not shock the product or spray water.
- Before using the product, eliminate the coating protection vinyl and sticker on the lighting panel and clean with a soft and clean piece of cloth.
- When you need go out for a long time
 - Set the dimming to the minimum or
 - Turn off the light and
 - Plug out from the socket
- If the product is damaged, do not use it at all. Please contact the company you brought the product.